BExBG05 Explosion Proof Xenon Beacon 5 Joule



The flameproof BExBG05 Xenon beacons are suitable for Zone 1, 2, 21 & 22 applications. Approved to IECEx, ATEX, Ex EAC and INMETRO standards.

The BExBG05 5 Joule beacons robust construction enables installation in the harshest of environments. Additional features include automatic synchronisation on multi-beacon systems and stainless steel guard and mounting bracket as standard.

The BEx range features enclosures manufactured from corrosion proof, marine grade copper free LM6 aluminium with a chromate and powder coat finish. All models have two M20 cable entries, large termination areas containing in & out terminals and an ingress protection of IP66/67.

Features

- Marine grade, corrosion proof, LM6 aluminium enclosure
- Automatic synchronisation on multi-beacon system.
- Beacons can be set to 'flip-flop' alternating mode with other units on multi-beacon systems.
- Xenon tubes mechanically secured against shock & vibration
- Glass lens & Stainless Steel guard
- Very large termination area.
- Dual M20 cable entries adaptors available.
- Stopping plug included.
- Ratchet adjustable stainless steel 'U' bracket.
- Reverse polarity diode fitted.
- IP66/67 ingress protection.
- 120 candela effective light intensity.
- UV stable PC, field replaceable, colour lens filter.

Approvals

• IECEx KEM 10.0002 X

IEC 60079-0:2011 IEC 60079-1: 2007-4 IEC 60079-31:2013

ATEX KEMA 00ATEX2 006X

EN 60079-0: 2012 + A11 EN 60079-1:2007 EN 60079-31:2014

TR-CU Ex EAC certificate: RU C-G B.AA71.B.00109

Safety-integrity level: SIL2

Inmetro certificate: 10-IEx-0010

Coding

- II 2G Ex d IIC T5 Gb Ta. -50°C to +45°C
- II 2G Ex d IIC T4 Gb Ta. -50°C to +70°C
- II 2D Ex tb IIIC T90°C Db Ta. -50°C to +40°C
- II 2D Ex tb IIIC T105°C Db Ta. -50°C to +55°C
- II 2D Ex tb IIIC T120°C Db Ta. -50°C to +70°C




















Specification

Energy:	5 Joules (5Ws)
Flash rate:	1Hz (60 fpm)
Peak Candela:	500,000 cd - calculated from energy (J)
Eff. Intensity cd:	250 cd - calculated from energy (J)
Peak Candela:	39,463 cd* - measured ref. to I.E.S.
Eff. Intensity cd:	120 cd* - measured ref. to I.E.S.
Lens colours:	Amber, Blue, Clear, Green, Red & Yellow
Voltages DC:	12 vdc; 2 4vdc; 48vdc
Voltages AC:	115vac; 230vac
Ingress protection:	BG 05D: IP66/67 BG 05E: IP66
Enclosure matl:	Marine grade copper free LM6 Aluminium
Enclosure finish:	Chromate & powder coated finish - anti-corrosion.
Colour:	RAL 3000 Red (others available on request)
Cable entries:	Dual M20 ISO (one stopping plug inc)
Terminals:	0.5 - 2.5mm² (20-14 AWG)
Enclosure volume:	<pre><2 litres</pre>
Line monitoring:	Blocking diode included EOL Min. 500 Ohm 2w, or 3k3 Ohm 0.5w resistor or diode (DC versions) can be fitted
Grounding stud:	M5
Temperature range:	-50° to +70°C (-58°F to +158°F)
Relative humidity:	90% at 20°C [68°F]
Tube life :	Emissions are reduced to 70% after 8 million flashes
Weight:	DC: 2.45kg/5.39lbs AC: 2.75kg/6.05lbs
Option S1:	SIL2 Compliant versions - contact E2S for technical info.

 $^{^{\}star}\text{All}$ candela data is representative of performance with clear lens at optimum voltage.

Part Codes

Version: Product type:	Part co	o de: Explosion proof 5J Xenon Beacon
Type:	DP	Ex d, UV stable PC Colour Lens
Voltage:	DC012 DC024 DC048 AC115 AC230	12 V dc 2 4V dc 48V dc 115V ac 2 40V ac
Cable Entry Type: [e] Note:	A B C D E F G	2 x M20x1.5mm 2 x 1/2" NPT - adaptors 2 x 3/4" NPT - adaptors 2 x M25x1.5mm - adaptors 1 x 1/2" NPT - adaptor 1 x 3/4" NPT - adaptor 1 x M25x1.5mm - adaptor M20 stopping plugs for unused entries supplied
Adaptor/Stopping plug material: [m]	B N S	Brass Nickel Plated Stainless Steel
Bracket/guard matl: [s]	1 2 3 4	A2 304 Stainless Steel A4 316 Stainless Steel A2 304 St/St with Equip. Tag A4 316 St/St with Equip. Tag (304)
Product version: [v]	A1 S1	Default - IECEx, ATEX, Ex EAC & INMETRO SIL2 - IECEx, ATEX, Ex EAC & INMETRO : 24Vdc only
Enclosure colour: [x]	R S	Red RAL3000 Special - contact E2S
Lens colour: [y]	A B C G M R	Amber Blue Clear Green Magenta Red Yellow

Current Consumption

our one concumption						
Version: 12 V dc		Voltage: 10-14V dc	Current: 750mA			
2 4V dc		20-28V dc	300mA			
48V dc		42-54V dc	180mA			
115V ac	50Hz/60Hz	+/-10%	140mA			
230V ac	50Hz/60Hz	+/-10%	55mA 8 Sep 2017			

E2S Warning Signals sales@e2s.com www.e2s.com